


HM7 Supercardioid Condenser Headset Microphone



General Product Description

The HM7 is an ideal hands-free microphone for singers, entertainers, back-up musicians and lecturers. Intended for use with wireless transmitters or wired phantom power, the HM7 offers brilliant sound quality with supercardioid response. An adjustable behind-the-head band secures the microphone while allowing complete freedom of movement. The HM7 also offers complete comfort and a contoured behind-the-head headband and flexible boom arm in an attractive nonreflective black matte finish. Precise placement can be obtained with the 4 mm diameter flexible gooseneck*.

* For best results, place the microphone with windscreen just touching the lips.



Specifications:

Frequency Response: 100 Hz - 15 kHz

Polar Pattern: Supercardioid

Generating Element: Back electret condenser

Sensitivity: 7 mV per Pascal

Maximum Input (3% THD): 120 dB SPL (3 wire)

Weight: 70 g

Accessories: Windscreen included
Connectors available per bodypack specs

Output Connector: Switchcraft TAF


Pin 1 Ground

Pin 2 Audio


Pin 3 Bias

Pin 4 No Connection





Frequency Response
 (Measured free field at 1 m with standard amplifier,
 1.3V supply and high impedance amplifier)



Polar Response
 (Measured at 1 kHz)

USA 12000 Portland Ave South, Burnsville, MN 55337, Phone: 952-884-4251, FAX: 952-884-0043
 Canada 705 Progress Avenue, Unit 46, Scarborough, Ontario, Canada, M1H2X1, Phone: 416-431-8875, 800-981-1005, FAX: 416-431-4588
 Germany Heudorfer Ring 45, D94315, Straubing, Germany, Phone: 49 9421-706 0, FAX: 49 9421-705 287
 France Parc de Courcette, Allé Lucie Willets, Lognon, 77185 Marne La Vallée, France, Phone: 331-6489-0990, FAX: 331-6485-0338
 Australia Unit 22, Block C, Sough Business Park, Sough Avenue, Sillanmeyer, N.S.W. 2128, Australia, Phone: 61-0-2048-3405, FAX: 61-0-2048-5505
 Hong Kong Unit E & F, 21/F, Luk Hop Industrial Bldg., 8 Luk Hop St., San PO Kong, Kowloon, Hong Kong, Phone: 852-2551-3628, FAX: 852-2551-3320
 Japan 5-3-8 Furubashi, Setagaya-ku, Tokyo, 156-0065 Japan, Phone: +81 (0) 3-5316-0320, FAX: +81 (0) 3-5316-0331
 Singapore 2055A Ubi Rd 1, 05-10, Kompong 120 Industrial Estate, Singapore 408726, Phone: 65-745-8700, FAX: 65-748-9206
 Mexico Av. Panaja Chapultepec #66-201, Col. El Parque Edo. Mex. 53360, Phone: 52-5358-5434, FAX: 52-5358-5588
 UK 4, The Willows Centre, Willow Lane, Mitham, Surrey CR4 6XK, UK, Phone: 44 181 642 9820, FAX: 44 181 646 7084
 Japan 12000 Portland Ave South, Burnsville, MN 55337, Phone: 952-887-7424, FAX: 952-887-0212
 Latin America 12000 Portland Ave South, Burnsville, MN 55337, Phone: 952-887-7424, FAX: 952-887-0212

© Telex Communications, Inc. 02/2001
 Part Number 38109-988 Rev A



ElectroVoice

U.S.A. and Canada only
 For customer orders, contact the Customer Service department at
 800/392-3497 Fax: 800/955-6631
 For warranty repair or service information, contact the Service
 Repair department at 800/685-2606
 For technical assistance, contact Technical Support at 866/78AUDI0
 Please refer to the Engineering Data Sheet for warranty information.
 Specifications subject to change without notice.

www.electrovoice.com • Telex Communications, Inc. • www.telex.com